

A quantum circuit for OR

Howard Barnum^(1,3), Herbert J. Bernstein⁽¹⁾, Lee Spector⁽²⁾

⁽¹⁾*School of Natural Science and ISIS, Hampshire College, Amherst, MA 01002, USA*

⁽²⁾*School of Cognitive Science, Hampshire College, Amherst, MA 01002, USA*

⁽³⁾*I.S.I. Foundation, Villa Gualino, Viale Settimio Severo 65, Torino 10133, ITALY*

email: {hbarnum, hbernstein, lspector}@hampshire.edu

(February 1, 2008)

We give the first quantum circuit for computing $f(0)$ OR $f(1)$ more reliably than is classically possible with a single evaluation of the function. OR therefore joins XOR (i.e. parity, $f(0) \oplus f(1)$) to give the full set of logical connectives (up to relabeling of inputs and outputs) for which there is quantum speedup. The XOR algorithm is of fundamental importance in quantum computation; our OR algorithm (found with the aid of genetic programming), may represent a new quantum computational effect, also useful as a “subroutine”.

All digital computing can be built out of Boolean functions. Suppose a physical process takes the two orthogonal inputs $|0\rangle, |1\rangle$ to outputs $|f(0)\rangle, |f(1)\rangle$, so that f is just a (classical) Boolean function from $\{0, 1\}$ to $\{0, 1\}$. This could be a quantum-coherent computer subroutine, or the evolution of some other physical system we are interested in [1]. If the process is a unitary quantum evolution, and we can prepare a desired state as input, then quantum computation lets one find out more about the function f than if we are restricted to evolution of classical states. For instance, we can find out its parity $f(0)$ XOR $f(1)$. The XOR circuit in [2] was the first concrete demonstration of quantum computation’s greater-than-classical power; the exact version in [3] is of fundamental importance in its own right and for its applications in more complex algorithms.

In this Letter, we complete the demonstration of quantum computation’s greater-than-classical power in this simple setting, by describing circuits which compute $f(0)$ OR $f(1)$ with one call to the subroutine f . While these circuits, unlike the XOR circuit, may err, we show that their performance is better than any possible classical circuit. This and XOR are the only quantum speedups in this simple domain. (NOR, AND, NAND, and NOT-XOR may also be sped up but they, and the algorithms that speed them up, are isomorphic to OR or XOR by simply relabeling of inputs and/or outputs.)

The OR algorithm represents a new quantum computational effect, which may have applications to more complex problems. Indeed, our circuits were derived as subroutines of a better-than-classical routine (evolved using genetic programming) to compute a more complex prop-

erty, “AND/OR,” of Boolean black-box functions of two variables ($f : \{0, 1\}^2 \rightarrow \{0, 1\}$). OR and AND/OR form part of an infinite family of properties (uniform binary AND/OR trees) whose quantum complexity is still imperfectly understood, but which have great theoretical and practical importance in computing, since they have applications in game tree evaluation, logic programming, theorem-proving, and many other areas, and their classical query complexity is completely understood.

The quantum complexity of Boolean properties of black-box functions has been studied in [4–6]. Here, we examine quantum gate arrays for certain properties of black box functions of one and two qubits. Given an unknown function f which may be called on particular inputs or coherently on superpositions of them, we wish to evaluate a Boolean property P of f . We are interested in p_{max}^e , the maximum over functions of the probability that an algorithm evaluates $P(f)$ incorrectly, and q_{max} , the maximum over functions of the expected number of function queries. *Exact* algorithms have $p_{max}^e = 0$; *Las Vegas* algorithms are correct whenever they answer 0 or 1, but may also answer “don’t know” with $p \leq 1/2$. *Monte Carlo* algorithms may err, but $p_{max}^e < 1/2$. The error is *one-sided* if there is a value x (0 or 1) such that $p_e = 0$ for f such that $P(f) = x$; otherwise it is *two-sided*. By n repetitions (and majority voting, for Monte Carlo), the latter two types may be made to have exponentially small (in n) probability of not giving the correct answer. Below, we use a definition in which Las Vegas algorithms may have stochastic runtime, but give correct answer with $p = 1$; DFP (described below) is an example. By running it repeatedly until an answer is obtained, the first type of Las Vegas algorithm may be converted into one of the second type with expected running time greater by a constant factor.

Genetic programming (GP) [7] evolves a population of programs (in our case, sequences of quantum gates) which are randomly mutated, recombined with each other, and preferentially selected for desired properties by running (or simulating) the programs on a sample of inputs. The repertoire of gates used by our GP engines (square brackets indicate qubit references, parentheses real parameters) was: HADAMARD[q], U-THETA[q](θ) := $\cos \theta I + i \sin \theta \sigma_y$, U2[q]($\alpha, \theta, \phi, \psi$) := $e^{i\alpha} e^{-i\phi \sigma_z} (\cos \theta I - i \sin \theta \sigma_y) e^{-i\psi \sigma_z}$; CNOT[control, target]; CPHASE[control, target](α) , which multiplies each

standard basis state by $e^{i\alpha}$ if it has 1 in both control and target positions; **ORACLE** $[q_1, \dots, q_n, q_{out}]$, which adds $(\text{mod } 2) f(q_1, \dots, q_n)$ to q_{out} , retaining $q_1, \dots, q_n$ unchanged; and **MEASURE-0** $[q]$ and **MEASURE-1** $[q]$, which measure qubit q in the standard basis. The **MEASURE- x** gates terminate the computation, returning the value x , if the measurement result x is obtained; if the result $\bar{x}$ is obtained, the state is projected onto the subspace with $|\bar{x}\rangle$ for that qubit, and computation proceeds.

Allowing termination conditional on intermediate results, as **MEASURE** gates do, makes the number of queries stochastic. For Monte Carlo algorithms, this yields at best a constant speedup over algorithms with a definite number of queries. Nevertheless, it may yield more perspicuous algorithms, and the constant speedup may be needed for better-than-classical performance, especially in the small- n regime.

For functions of binary strings of length d , the AND/OR problem is to evaluate a binary tree, having AND at the root and d layers of alternating OR and AND as nodes, with a $d+1$ st layer of $n \equiv 2^d$ leaves consisting of the values of the black-box function ordered by their input string (viewed as a binary integer). This and related problems have many applications, for example in game-tree evaluation, dynamic programming, waveform analysis, and theorem-proving. Saks and Wigderson showed that “depth-first pruning” (DFP) is the best classical Las Vegas algorithm for AND/OR [8]. DFP uses a routine **eval**(node) which returns the value of the node if it is a leaf, and otherwise randomly chooses a daughter of the node and calls itself on the subtree rooted at that daughter. If this call returns a value for the subtree that determines the value of the node (1 if it is an OR node, 0 if it is an AND node), **eval** returns the appropriate value; otherwise it calls itself on the other highest-level subtree of the node, and returns the value of that subtree. DFP itself just calls **eval**(root).

Santha [9] showed, for read-once Boolean functions (for which there is a Boolean formula containing each variable at most once), that no classical Monte Carlo algorithm with all error probabilities below p can have expected queries $q < (1 - xp)Q$, where Q is the time taken by the optimal Las Vegas algorithm, and $x = 1, 2$ as the error is one- or two-sided. (It is not known whether a quantum analogue of this holds.) This is just the trivial speedup obtained by flipping a biased coin to decide whether to do the optimal Las Vegas algorithm or output a random bit (two-sided) or a zero (one-sided). Thus a q -query quantum algorithm would have to have $p_{max}^e < \frac{1}{x}(1 - \frac{q}{Q})$ to be better-than-classical. DFP has worst-case expected queries 3 for depth-two AND/OR, so a one-query quantum algorithm would need $p < 1/3$ two-sided, $p < 2/3$ one-sided to do better than classical. There is no one-query, zero-error quantum strategy for calculating OR for a black box Boolean function of one bit [10,4]. DFP has expected queries 3/2, so a one-query quantum algo-

rithm with $p < 1/6$ two-sided or $p < 1/3$ one-sided would be better than classical.

Our OR circuit is shown in Fig. 2. We use the convention that the leftmost qubit in a ket or string of kets is qubit 0, the next qubit 1, and so on. Before the **MEASURE-1** gate on qubit 0, the state is:

$$(1/2) [|0\rangle(|f_0\rangle + |f_1\rangle) + |1\rangle(|f_0\rangle - |f_1\rangle)] . \quad (1)$$

Thus the **MEASURE-1** has $p = 0$ for outcome 1 if $f_0 = f_1$ (even parity), due to destructive interference, while if the parity is odd, it has $p = 1/2$ of correctly yielding 1 ($|f_0\rangle$ and $|f_1\rangle$ are orthogonal, and do not interfere). If the computation does not halt, the state becomes:

$$(1/2)|0\rangle(|f_0\rangle + |f_1\rangle) . \quad (2)$$

Its squared norm is the probability that the **MEASURE-1** gate yielded 0. First consider $\theta = 0$. For the even parity cases, this term gives the correct answer, while for the odd parity cases, it is equally likely to give either answer; it contributes $1/4$ to p_e . Thus $p_e^{00} = p_e^{11} = 0$, and $p_e^{01} = p_e^{10} = 1/4$. The error is one-sided, so it is better than classical ($p_e^{max} < 1/3$). (If we had not halted the computation when the measurement of qubit 0 yielded 0, and had measured qubit 1 in the eigenbasis of σ_x instead of the σ_z -eigenbasis used in the $\theta = 0$ version of our algorithm, one sees from (1) that a value of 0 for the final measurement means the value of the first measurement gives the parity, while a value 1 for the final measurement means the value of the first measurement is noise. This is Deutsch’s Las Vegas algorithm for parity [2].) Our algorithm also outperforms attempts to use 2-alternative Grover search to evaluate OR; despite that method being asymptotically optimal for OR of many inputs, it does not perform better than classically in this instance. Adding an $X(\theta)$ before the final measurement gives: $p_e^{odd} = 1/2 + (\frac{c-s}{2})^2$, $p_e^{even} = s^2$. Equating these gives a solution $c = \frac{-3}{\sqrt{10}}$, $s = \frac{1}{\sqrt{10}}$ with $p_e = 0.1$ for all cases. Since $p_e < 1/6$ two-sided with one query, this is also better than classical.

To see that the $\theta = 0$ array for OR minimizes p_{max}^e subject to the constraint $p_{00}^e = p_{11}^e = 0$, consider the state just before the black-box function is queried:

$$|\Psi\rangle = |\psi_{00}\rangle|00\rangle + |\psi_{01}\rangle|01\rangle + |\psi_{10}\rangle|10\rangle + |\psi_{11}\rangle|11\rangle . \quad (3)$$

The right-hand ket in each term is a state of the two qubits on which the function will be called, and $\sum_{ij} \langle \psi_{ij} | \psi_{ij} \rangle = 1$. After the query, the state is:

$$|\psi_{00}\rangle|0f(0)\rangle + |\psi_{01}\rangle|0\overline{f(0)}\rangle + |\psi_{10}\rangle|1f(1)\rangle + |\psi_{11}\rangle|1\overline{f(1)}\rangle .$$

The four functions of one bit give states $|0\rangle, |1\rangle, |2\rangle, |3\rangle$. We have:

$$\langle 0|1\rangle = \langle \psi_{00} | \psi_{00} \rangle + \langle \psi_{01} | \psi_{01} \rangle + 2\text{Re}\langle \psi_{10} | \psi_{11} \rangle . \quad (4)$$

$$\langle 0|2\rangle = \langle \psi_{11} | \psi_{11} \rangle + \langle \psi_{10} | \psi_{10} \rangle + 2\text{Re}\langle \psi_{00} | \psi_{01} \rangle . \quad (5)$$

$$\langle 0|3\rangle = 2\text{Re}\langle \psi_{00} | \psi_{01} \rangle + 2\text{Re}\langle \psi_{10} | \psi_{11} \rangle . \quad (6)$$

Requiring $p_{11}^e = 0$ and thus $\langle 0|3\rangle = 0$, there are optimal algorithms which measure $|0\rangle\langle 0|$ and $I - |0\rangle\langle 0|$. For these, $p_e^{max} = \max_{j=1,2,3} |\langle 0|j\rangle|^2$. A simple calculation using the Schwarz inequality and $\sum_{ij} \langle \psi_{ij} | \psi_{ij} \rangle = 1$ shows that p_{max}^e is minimized where $\langle 0|2\rangle = \langle 0|3\rangle = 1/2$, at $p_{max}^e = 1/4$.

For our algorithm $\langle 0|3\rangle = \langle 1|2\rangle = 0$, while the other inner products are $1/2$. The states span a 3-d real subspace of the 4-d complex space of two qubits. They lie, evenly spaced, on a cone with apex at the origin and opening angle $\pi/2$. The rest of the algorithm measures three orthogonal subspaces: $\{|10\rangle, |11\rangle\}$ (outcome 1 for MEASURE-1 0 ; algorithm returns 1), $\{|00\rangle\}$ (outcome 0 for final measurement on qubit 1; algorithm returns 0), and $\{|01\rangle\}$ (outcome 1 for final measurement on qubit 1; algorithm returns 1). The outcome 1 for the algorithm corresponds to the 3-d subspace perpendicular to $|00\rangle$, while the outcome 0 corresponds to $\{|00\rangle\}$. When MEASURE-1 0 yields 1, qubit 1 lies along $|0\rangle - |1\rangle$, so within the 3-d space spanned by the possible computer states the outcome “1” for MEASURE-1 0 involves one dimension, and the result “1” for the algorithm two dimensions. Our algorithm makes a further finegrained measurement within these two dimensions, but we may avoid this (which could affect the results when the routine is called recursively) by converting it into one which measures a single qubit at the end. Such an algorithm is: HADAMARD 0 ; ORACLE 0 1 ; HADAMARD 0 ; CHADAMARD 0 1 ; CONTROLLED X-THETA 0 1 θ ; MEASURE-0 1 ; MEASURE-1 1.

The OR algorithm was derived by restriction from a larger algorithm found via genetic programming. This algorithm computes the depth-two case (AND/OR₂) of evaluating:

$$(f(00) \vee f(01)) \wedge (f(10) \vee f(11)) .$$

With the number of oracle calls fixed at one, and selection to minimize p_{max}^e , GP yielded the algorithm reported in [11], where more detail on the GP engine used to evolve it may also be found.

Hand simplification and improvement yielded the gate array of Fig 1. Here X(θ) has the matrix ($c := \cos \theta, s := \sin \theta, \theta = .0749\dots$):

$$\begin{bmatrix} c & s \\ s & -c \end{bmatrix} .$$

This algorithm has error probabilities constant on orbits of the automorphism group, given in Table I.

Orbit	p_e	Orbit	p_e
0 0 0 0	.00560	0 1 0 1	.28731
0 0 0 1	.28731	1 1 0 1	.21269
0 0 1 1	.21269	1 1 1 1	.00560

Table I: Error probabilities (to 5 digits) for hand-tuned simplified AND/OR algorithm

The *automorphism group* of a property P consists of those permutations σ of its input variables which leave its value invariant for all assignments (all black-box functions). AND/OR₂ has four input variables $f_0 \equiv f(00), f_1 \equiv f(01), f_2, f_3$; its automorphism group is generated by $(0 \leftrightarrow 1), (2 \leftrightarrow 3), (0 \leftrightarrow 2, 1 \leftrightarrow 3)$. $Aut(P)$ acts on functions via $f^\sigma(x) := f(\sigma(x))$. For AND/OR₂, the orbits of this action may be labeled by representative functions (written as strings $f_0 f_1 f_2 f_3$): 0000₁, 0001₄, 0011₂, 0101₄, 1101₄, 1111₁. Subscripts indicate the number of functions in the orbit. Our algorithm also has this automorphism group: the outcome probabilities for all its measurement gates are constant on orbits of the group. It is better than classical, since $p_e^{max} < 1/3$.

The structure of the algorithm suggests examining its restriction to qubit 1, since the states with 0 versus 1 input in qubit 0 are still orthogonal when qubit 1 is measured, so don't interfere. If we fix the input for qubit 0 at 0 and remove qubit 0 from the algorithm we may consider the algorithm to use only two qubits and to apply to a new function $\tilde{f} := f(0\cdot)$ defined by $\tilde{f}(0) = f(00)$ and $\tilde{f}(1) = f(01)$. Relabeling qubit 1 as 0, qubit 2 as 1 and $\tilde{f}$ as f , we get the circuit of Fig. 2 for computing $f(0)$ OR $f(1)$.

Similarly, fix a value x for qubit 1 in the depth-two algorithm and view it as an algorithm for AND operating on the one-bit function $f_x(y)$ given by $f(xy)$. This is not identical to the array derived by applying De Morgan's law ($\text{NOT}-(\text{NOT}-A \text{ OR } \text{NOT}-B) \equiv A \text{ AND } B$) to our OR algorithm, but its action on all black-box functions is the same. So the depth-two algorithm can be loosely viewed as a “recursive” application of the depth-one algorithm (modified to give AND at the top level). Loosely speaking, it superposes values for qubit 0 (as in the AND algorithm), and calls a “function” of qubit 1; which function depends on qubit 0. This is not quite accurate for two reasons. First, the lower-level algorithm returns a value to the upper level only if the MEASURE-1 1 does not halt the computation. If MEASURE-1 1 halts the computation, the superposition of qubit-0 values provides a random value for that bit; the lower level algorithm is effectively called on a randomly chosen marginal black-box function, and the result returned as our algorithm's final output. Second, if the lower-level “function call” is not halted the “function” of i called by the top-level AND routine has an $f(i\cdot)$ -dependent 4×4 unitary matrix which is not of the usual black-box form. The state after the function call and second HADAMARD 1 is:

$$(1/2\sqrt{2}) [|00\rangle(|f_{00}\rangle + |f_{01}\rangle) + |01\rangle(|f_{00}\rangle - |f_{01}\rangle) \\ - |10\rangle(|f_{10}\rangle + |f_{11}\rangle) - |11\rangle(|f_{10}\rangle - |f_{11}\rangle)] . \quad (7)$$

This is a superposition, with coefficients $1/\sqrt{2}$ and $-1/\sqrt{2}$, of states of the form (1) of qubits 1 and 2, with the qubit 0 recording which marginal black box function, $f(0\cdot)$ or $f(1\cdot)$, is involved.

When $f(00) \neq f(01)$ or $f(10) \neq f(11)$, but not both; (orbits 1101_4 and 0001_4), the **MEASURE-1** has $p = 1/4$ of halting the computation with result 1, an error if the orbit is 0001 . If both subtrees have odd parity (0101_4 only), $p = 1/2$ of halting and (correctly) yielding 1, and if neither does (0000 , 1111 , 0011_2), $p = 0$. This measurement contributes $1/4$ to p_{0001}^e .

The state after the **MEASURE-1** gate yields 0 is given by the terms with $|00\rangle$ and $|01\rangle$ in (7). Hadamarding qubit 0 yields:

$$(1/4) [|00\rangle(|f_{00}\rangle + |f_{01}\rangle - |f_{10}\rangle - |f_{11}\rangle) + |10\rangle(|f_{00}\rangle + |f_{01}\rangle + |f_{10}\rangle + |f_{11}\rangle)] . \quad (8)$$

The **MEASURE-0** gate will terminate the computation with the result 0 with probability given by the squared norm of the first term in this state. If measurement yields 1, the final state is given by the second term in (8). Then the probability of the final measurement on qubit 2 giving $1(0)$ is

$$(1/16)(n_{1(0)}(f))^2 , \quad (9)$$

where $n_x(f)$ is the number of inputs on which f takes the value x . The total error probabilities (with their sources) are:

Orbit	Error probability
0 0 0 0	0
0 0 0 1	$1/4 (M-1 \ 0) + 1/16 (M-1 \ 2) = 5/16$
0 0 1 1	$1/4 (M-1 \ 2)$ 1/4
1 1 0 1	$1/8 (M-0 \ 1) + 1/16 (M-0 \ 2) = 3/16$
0 1 0 1	$1/4 (M-0 \ 2)$ 1/4
1 1 1 1	0

This is better than classical even without the final $X(\theta)$. For 0001 , 1101 , 0101 the final measurement may give either result. We may decrease p_{max}^e (here p_{0001}^e) by increasing the likelihood that the final measurement yields 0, at the cost of increasing p_{0101}^e and p_{1101}^e for which $P(f) = 1$, and also possibly p_{0000}^e and p_{1111}^e . Thus, consider adding, before the measurement, an $X(\theta)$ gate on qubit 2. We obtain $p_{0001} = (\frac{3s-c}{4})^2 + \frac{1}{4}$, $p_{0101} = (\frac{c+s}{2})^2$. Equating these gives $s^2 = (9 - 14\sqrt{2/5})/26$, so $\theta^* = 0.074909\dots$ at $p_e = p_{0001} = p_{0101} = 0.287315\dots$

With the help of genetic programming, we found better-than-classical quantum gate arrays for the depth one and two cases of the family of properties of black-box functions given by alternating binary AND/OR trees. These circuits could constitute small- n instances of a scalable Monte Carlo algorithm for this family of properties. They are also small- n instances of the bounded-depth AND/OR tree problems whose complexity was characterized in [5,6]. The Grover-based algorithms therein achieve marked speedups over classical means in the large- n regime, as the fan-in of the nodes in the

bounded-depth trees grows; their $n = 2$ and $n = 4$ instances are not superclassical. In contrast, our arrays give speedups for fan-in 2. Since the uniform binary tree problem has fan-in 2 for all instances, this suggests that aspects of our gate arrays may prove useful in addressing this problem even for large n . If so, this would be another new quantum computational effect related to the OR circuit. As it stands, OR joins XOR to complete the set of logical properties of one-bit black-box subroutines which can be quantum-mechanically computed, with one subroutine call, more reliably than is classically possible.

ACKNOWLEDGMENTS

Supported in part by the John D. and Catherine T. MacArthur Foundation's MacArthur Chair program at Hampshire College, by NSF grant #PHY-9722614, and by a grant from the ISI Foundation, Turin, Italy, and the Elsag-Bailey corporation. We thank H. Burhman, R. Cleve, M. Mosca, and R. de Wolf for discussions.

-
- [1] A. M. Childs, J. Preskill, and J. Renes, (1999), Los Alamos ArXiv Preprint Archive quant-ph/9904021.
 - [2] D. Deutsch, Proc R Soc London A **400**, 97 (1985).
 - [3] R. Cleve, A. Ekert, C. Macchiavello, and M. Mosca, Proc R Soc Lon A **454**, 339 (1998).
 - [4] R. Beals, H. Buhrman, R. Cleve, M. Mosca, and R. de Wolf, FOCS '98 352 (1998).
 - [5] H. Buhrman, R. Cleve, and A. Wigderson, Proceedings of the 30th Annual ACM Symposium on the Theory of Computing (STOC) 63 (1998).
 - [6] H. Buhrman, R. Cleve, R. de Wolf, and C. Zalka, (1999), Los Alamos ArXiv Preprint Archive cs.CC 9904019.
 - [7] J. R. Koza, *Genetic Programming: On the Programming of Computers by Means of Natural Selection* (The MIT Press, Cambridge, MA, 1992).
 - [8] M. Saks and A. Wigderson, Proceedings of the 27th IEEE Symposium on the Foundations of Computer Science (FOCS) 29 (1986).
 - [9] M. Santha, Proceedings of the 6th IEEE Structure in Complexity Theory 180 (1991).
 - [10] R. Jozsa, Proc R Soc London A **435**, 563 (1991).
 - [11] L. Spector, H. Barnum, H. Bernstein, and N. Swamy, in *Advances in Genetic Programming* (MIT Press, Cambridge, MA, to appear in 1999), Vol. III.




FIG. 1. Hand-tuned version of evolved AND/OR; $\theta = 0.74909\dots$




FIG. 2. An algorithm for OR